

SONY®

Network Video Management System

License Guide

HAW Series

SOW Series


Table of Contents

Introduction	3
Applying Licenses	4
Step 1: Registering the SLC and Acquiring the License File	5
Step 2: Applying Additional Licenses	6
Steps 3, 4, and 5: Installing Applications, Importing License Files, and Configuring Application Settings	7
Step 6: Activating the License	7
eCSite User Registration	9
Version Upgrades	10
Version Downgrades (HAW Standard Edition Only)	11
Transferring Device Licenses (HAW Enterprise Edition Only).....	12
Regional Contact Information	13
Number of Device Changes without Activation	14

Introduction

This document describes how to perform operations related to licenses, including how to register the software license code (SLC), acquire the license file, and activate the license. The various manuals referenced in this document are available at the following URL.
<https://www.sony.net/CameraSystem/NVMS/Manuals>

Applying Licenses



*1 A step for importing licenses is included during application installation for the SOW Enterprise Edition.

Note

For details on applying licenses for the HAW Standard Edition and HAW Enterprise Edition, refer to the unit installation manual first.

Step 1: Registering the SLC and Acquiring the License File

To acquire the license file, you must register the SLC with Bosch Security Systems. When you email to Bosch Security Systems with the following information, the license file will be sent to you from the company. For contact details in each region, see "Regional Contact Information " (page 13).

For details on importing the acquired license file to applications, refer to the Network Video Management System Administrator Manual for the SOW series or the installation manual for the HAW series.


Caution

Registration of the SLC and application of additional licenses may take about 1 business day to complete. We recommend scheduling and performing installation with this in mind and ensuring sufficient leeway.


The information to be sent to Bosch Security Systems

Your contact information	Name	
	Company Name	
	E-mail address	
Product information	Product Name	
	SLC	This can be found on the License Purchase Notification or on the label on the rear of the unit.
	Authorization code (If you have the additional license to be applied)	See Step 2 also.

License Purchase Notification



HAW unit bottom



Step 2: Applying Additional Licenses

If you purchased any additional licenses, the additional licenses must be applied to license you are using.

License Purchase Notification (for additional licenses)

Sony Corporation ソニー株式会社	
LICENSE PURCHASE NOTIFICATION ライセンス購入通知書	
Order ID / 注文ID	00000000000000000000
Order No. / 注文番号	123456
Product Category / 製品カテゴリ	VMS Standard Edition
Product Name (Version) / 製品名(バージョン)	SOWA-SS01 WW
Software Name / ソフトウェア名	1 year SUP for SOW Standard Edition 1ch license
Sales Company / 販売会社	SBSC
Serial Number / 製品番号	0000112233
Authorization Code / 認証コード	S-6452-88VW-7NT83

This is to notify Sony's sales company of the Software Purchase Key. In accordance with necessity, please prepare the install key and the Software from following URL. For the key required, information of the Customer and the device entry is required.

これはソニーの営業会社へソフトウェア購入キーの届出を通知するための通知書です。必要に応じてインストールキーとソフトウェアを以下のURLからダウンロードしてください。必要なキー情報は、お客様の情報とデバイス登録情報が必要です。

ソニー株式会社
Sony Corporation

When you contact Bosch Security Systems with the SLC you are using and the authentication code found on the license certificate of the additional license, the appropriate license file for the additional license SUP will be sent to you. For contact details in each region, see "Regional Contact Information" (page 13).

When extending your SUP, the additional licenses for all the SUPs that cover your system must be applied at the same time.

Example:

When using SOW Standard Edition and 64ch additional licenses

The "1 year SUP for SOW Standard Base license" and the "1 year SUP for SOW Standard Edition 32ch licenses" (×2) must be applied at the same time.

Caution

Registration of the SLC and application of additional licenses may take about 1 business day to complete. We recommend starting the actual installation work when you have a sufficient amount of time to spare.

Steps 3, 4, and 5: Installing Applications, Importing License Files, and Configuring Application Settings

For details on the procedures, refer to the Network Video Management System Administrator Manual for the SOW series or the installation manual for the HAW series.

Step 6: Activating the License

After registering cameras and configuring settings with the application, you must activate the license. To activate the license, you must access the Sony license website, eCSite, via a web browser.

1. Export the LRQ file from the application.
The LRQ file is necessary to perform activation. For details on exporting the LRQ file, refer to the Network Video Management System Administrator Manual for the SOW series or the installation manual for the HAW series.
2. Start the web browser on the computer.
3. Enter the following URL in the address bar of the web browser.
`https://www.ecspert.sony.biz/`
The eCSite login screen appears.


Note

Use Internet Explorer 10 or later to access eCSite.

4. Enter the user ID and password, and click [Login].
If you are logging in for the first time since eCSite's renewal, user registration will be required.

For details, see "eCSite User Registration" (page 9). The user ID can be found in the eCSite email notification that indicates that user registration is complete. For the password, enter the

password configured during eCSite user registration.



5. Enter the access code, and click [Login].

The access code can be found in the eCSite email notification that indicates that user registration is complete.



The home screen appears.


6. Click [NVMS License Management System] on the left side of the screen.



7. Activate the license.

- 1) Click the [Browse] button to display the file selection dialog box. Select the LRQ file you exported from the application.
- 2) Click [Activate] to start activation. When activation is successfully completed, click [Save] in the file downloading dialog box that appears to save the file.
- 3) Import the saved file to the application. For details on importing, refer to the Network Video Management System Administrator Manual for the SOW series or the installation

manual for the HAW series.



eCSite User Registration

1. Click [User Registration] at the bottom right of the login screen.
2. Enter an email address and password in the user registration screen that appears, and click [Registration].
The password must be 8 to 16 characters in length and contain at least one each of numbers (0 to 9), lowercase letters (a to z), and uppercase letters (A to B).
3. When you receive the email notification of registration completion, access the URL found inside.
Be sure to access the site within 24 hours of receiving the email. When the user registration completion screen appears, click [Login] (blue text) at the top left of the screen to display the login screen.

Caution

The user ID and access code found in the email notification of registration completion will be necessary during login.

Version Upgrades

A new SLC must be issued when you upgrade the application versions. For details, contact your Sony sales company.

Version Downgrades (HAW Standard Edition Only)

A new SLC must be issued when you downgrade the application versions. For details, contact your Sony sales company.

Transferring Device Licenses (HAW Enterprise Edition Only)

When configuring a system with multiple HAW Enterprise Edition units, the device license associated with the SLC from at the time of purchase must be transferred to the other SLC. For details on transferring device licenses, contact your Sony sales company. Information on the pre-transfer and post-transfer SLC will be required when you do so.

Regional Contact Information

Contact Information	Region	Contact
Bosch Security Systems	WW	SonyNVMSLicense@bosch.com

Number of Device Changes without Activation

The three variables (C%, Cmin, Cmax) that are found in the Network Video Management System Administrator Manual and used for calculating the number of device changes without activation are configured as follows for each installation of the software.

	C%	Cmin	Cmax
SOW Standard Edition HAW Standard Edition	15%	2	4
SOW Enterprise Edition HAW Enterprise Edition	15%	10	100